

## Double relays WIFI mains voltage

CODE: OMN500

OMNI is an innovative light control system that combines "wired" technology with modern software for controlling functions via Wifi and also with voice assistants.

It will thus be possible to control the light from a normal ON / OFF button (N.A.), from your smartphone, tablet or your favorite voice assistant.

The connection to the WiFi network is very simple via Bluetooth connection, therefore it does not require the pairing procedure.

The system configuration, any changes in the combinations, the creation of scenarios will be so simple.

Device with double SSR relay output in 230V alternating voltage.

Controllable via Wifi


Allows you to drive 2 loads independently.

Simple connection to the Wifi network via Bluetooth connection (no pairing required)

Entrances

- 2 x non-insulated buttons
- 1 x Wifi
- Controllable via proprietary app for Android / IOS / Windows via Amazon Alexa voice assistant and Google Assistant

- IP20, for indoor use
- Operating temperature: -40 ° C + 60 ° C



## Technical data

Article	Volt	Max power	Current	Size (mm)	N. output
OMN500	110-240V AC	480W (24V)	2A/canale	40x80x24,5	2

## Data sheets

